

# BiBurst | OPTION

## Tunable GHz and MHz Burst with Burst-in-Burst Capability

PHAROS and CARBIDE-CB3 lasers offer an option for tunable GHz and MHz burst with burst-in-burst capability, known as BiBurst.

In standard mode, a single pulse is emitted at a fixed frequency. In burst mode, the output consists of pulse packets rather than single pulses. Each packet comprises a certain number of equally spaced pulses. MHz-Burst contains N pulses with a nanosecond period, while GHz-Burst contains P pulses with a picosecond period. When both GHz and MHz burst modes are used simultaneously, the equally spaced pulse packets contain sub-packets of pulses, known as burst-in-burst or BiBurst.

PHAROS and CARBIDE lasers with the BiBurst option bring new capabilities to high-tech manufacturing industries such as consumer electronics, integrated photonic chip manufacturing, future display manufacturing, and quantum technologies. The applications include:

- brittle material drilling and cutting
- deep engraving
- selective ablation
- volume modification of transparent materials
- hidden marking
- surface polishing
- functional surface structuring

### Specifications

Model		CARBIDE-CB3	PHAROS
GHz Burst	Intra burst pulse period <sup>1)</sup>	440 ± 40 ps	200 ± 40 ps
	Number of pulses, P <sup>2)</sup>	1 – 10 <sup>3)</sup>	1 – 25
MHz Burst	Intra burst pulse period	≈ 15 ns	
	Number of pulses, N	1 – 10	1 – 9 (7 with FEC <sup>4)</sup> )

<sup>1)</sup> Custom spacing is available upon request.

<sup>2)</sup> The maximum number of pulses in a burst depends on the laser repetition rate and energy.

<sup>3)</sup> A custom number of pulses (up to 400) is available upon request.

<sup>4)</sup> Fast energy control option. Enables the formation of any pulse envelope at the laser pulse repetition rate.

